



## Instructions for finding alternate assembly number (AA#), BIOS version, and Intel® ME firmware version

During boot, enter the BIOS setup by pressing **F2**.

The board's current BIOS version is shown at the top of the **Main** menu. Then click **System Identification Information**.

System Setup	
Main	Configuration Performance Security Power Boot Exit
BIOS Version	BLH6710H.86A.0076.2010.1115.1959
Processor Type	Intel(R) Core(TM) i3-2120 CPU @ 3.30GHz
Active Processor Cores	<ALL>
Intel® Hyper-Threading Technology	<Enable>
Host Clock Frequency	100 MHz
Processor Turbo Speed	3.30 GHz
Memory Speed	1333 MHz
L2 Cache RAM	2 x 256 KB
L3 Cache RAM	3 MB
Total Memory	1 GB
DIMM3 (Memory Channel A Slot 0)	Not Installed
DIMM1 (Memory Channel A Slot 1)	1 GB
DIMM4 (Memory Channel B Slot 0)	Not Installed
DIMM2 (Memory Channel B Slot 1)	Not Installed
<u>System Identification Information</u>	
System Date	<Wed 01/25/2012>
System Time	<02:44:09>

The board's AA# and Intel® ME firmware version are shown on the **System Identification Information** screen.

System Setup	
Main	
System Identification Information	
System Information	
Manufacturer	
Product Name	
Version	
Serial Number	
UUID	7E9D8539-2668-E011-A698-00E04CA04AED
Desktop Board Information	
Manufacturer	Intel Corporation
Product Name	DH67BI
Version	AAG10189-205
Serial Number	BTBL1160030Z
Chassis Information	
Manufacturer	
Version	
Serial Number	
Asset Tag	
Processor Signature	000206A7
	Family 6h Model 2Ah Stepping 7h
Microcode Update Revision	00000006
Onboard LAN MAC Address	E0-69-95-72-0F-1D
<u>Intel® Management Engine Information</u>	
Intel® Management Engine Firmware	7.0.1.1141

**Table 1**

<b>Board</b>	<b>22nm-Ready AA#s</b>	<b>22nm-Capable AA#s</b>	<b>22nm-Transition BIOS version</b>	<b>22nm-Ready BIOS version</b>
DZ68DB	AAG27985-TBD	AAG27985- TBD	DBZ6810H.86A. TBD	DBZ6810H.86A. TBD
DZ68BC	AAG30742- TBD	AAG30742- TBD	BCZ6810H.86A. TBD	BCZ6810H.86A. TBD
DZ68ZV	AAG41861- 302	AAG41861-301	BGP6810H.86A.2111	BGP6810H.86A.2161
DP67BG	AAG10491- 401	AAG10491-400	BGP6810H.86A.2111	BGP6810H.86A.2161
DP67DE	AAG10217- TBD	AAG10217- TBD	BAP6710H.86A. TBD	BAP6710H.86A. TBD
DP67BA	AAG10219- TBD	AAG10219- TBD	BAP6710H.86A. TBD	BAP6710H.86A. TBD
DH67CL	AAG10212-210	AAG10212-206	BLH6710H.86A.0132	BLH6710H.86A.0146 or later
DH67CF	AAG10215-207	AAG10215-204	BLH6710H.86A.0132	BLH6710H.86A.0146 or later
DH67BL	AAG10189-211	AAG10189-206	BLH6710H.86A.0132	BLH6710H.86A.0146 or later
DH67BLR	AAG44434-201	All	BLH6710H.86A.0132	BLH6710H.86A.0146 or later
DH61ZE	AAG43004-201	All	BEH6110H.86A.0035	BEH6110H.86A.0038 or later
DH61WW	AAG23116-206	AAG23116-204	BEH6110H.86A.0035	BEH6110H.86A.0038 or later
LADH61WW	AAG39552-206	AAG39552-204	BEH6110H.86A.0035	BEH6110H.86A.0038 or later
DH61SA	AAG38870-204	All	BEH6110H.86A.0035	BEH6110H.86A.0038 or later
LADH61SA	AAG38871-204	All	BEH6110H.86A.0035	BEH6110H.86A.0038 or later
LADH61SAR	AAG44435-202	All	BEH6110H.86A.0035	BEH6110H.86A.0038 or later
DH61DL	AAG14066-205	All	BEH6110H.86A.0035	BEH6110H.86A.0038 or later
DH61CR	AAG14064-207	AAG14064-204	BEH6110H.86A.0035	BEH6110H.86A.0038 or later
DH61BE	AAG14062-209	AAG14062-206	BEH6110H.86A.0035	BEH6110H.86A.0038 or later
DH61AG	AAG23736-TBD	AAG23736-TBD	AGH6110H.86A. TBD	AGH6110H.86A. TBD

The following Intel® Desktop Boards will not include support for future 22nm processors:

- DH61KVCH
- DH61SKCH
- DB65AL
- DH67VR
- DQ67SW
- DQ67OW
- DQ67EP